

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 3

Amendments to the Claims

This listing of claims will replace all prior versions, and listing, of claims in this application.

Listing of Claims:

1. (Currently amended) A fractional-spaced digital equalizer comprising:
 - a bank of register delay elements representing [the] a data register bank that stores [those] samples of [the] an input distorted waveform;
 - a switch S1 to control [that] a portion of [the] a joint ISI-canceling and MF equalizer update associated with [the] an ISI-cancellation process;
 - a bank of register elements representing equalizer FF weight register bank that stores [the] equalizer FF weights coefficient values;
 - a bank of multiplier elements used in forming [the] inner products associated with both the ISI-cancellation and MF constraint updates;
 - a bank of summing nodes used in forming [the] inner products associated with both the ISI-cancellation and MF constraint updates;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 4

an M:1 commutation device to perform decimation to the symbol rate;

an algorithm to form the error sequence associated with ISI cancellation;

an algorithm to convert [the] an ISI cancellation error signal into an adjustment signal needed to control [the] an equalizer FF weight update in accordance with [the] a criterion for ISI cancellation;

an algorithm to update the contents of the equalizer FF weight register bank in accordance with first, the criterion for ISI-cancellation, and second, [the] a MF constraint criterion;

a bank of register elements representing the constraint register bank to store samples of the constraint waveform;

an algorithm that generates samples of [a] the constraint waveform;

[a] the constraint waveform used in forming the inner product associated with the MF constraint processing;

a switch S2 to control that portion of the joint ISI-canceling and MF equalizer update associated with the MF constraint process;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 5

a parameter β representing the constraint level of the MF constraint update;

a differencing node to subtract the orthogonality measure from the constraint level in order to form the constraint error; and

an algorithm to convert the constraint error signal into an adjustment signal needed to control the equalizer FF weight update in accordance with the MF constraint criterion;

2. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein said equalizer operates at M-samples-per-symbol where $M > 1$ and satisfies the Nyquist Criterion.

3. (currently amended) The fractional-spaced equalizer as set forth in claim 2 wherein said sampling factor M is equal to 2.

4. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein said equalizer operates as a complex equalizer comprising complex operations;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 6

5. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein said equalizer operates as a real equalizer comprising real operations;

6. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein the signal occurring prior to said M-to-1 decimator is passed directly to switch S2, instead of passing through said M-to-1 commutator, so that constraint processing can be performed using every fractional-spaced sample of the distorted input waveform;

7. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein said algorithm that computes the error associated with ISI-cancellation is based upon a training sequence update and comprises:

a training sequence of distortion-less data; and

a differencing node to form the difference between the equalized decimated signal and the training sequence;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 7

8. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein said algorithm that computes the error associated with ISI cancellation is based upon a decision-directed update and comprises:

a slicer device to quantize samples of equalized decimated signal; and

a differencing node to form the difference between pre-slicer sequence and post-slicer sequence;

9. (currently amended) The fractional-spaced equalizer as set forth in claim 1 wherein said algorithm that computes the error associated with ISI cancellation is based upon [the] a blind CMA update and comprises:

an algorithm to form the statistical parameter R_m measuring the ratio of moments of the pre-pulse shaped modulation amplitudes;

a switch $S7$ to eliminate the computation of R_m from the processing so that parameter R_m is computed only one time;

a register element to store the value of parameter R_m ;

a complex conjugation operator to conjugate the sample input to the CMA;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 8

a multiplier element to obtain the product between the input sample and its complex conjugate;

a differencing node to form the difference between parameter R_m and the absolute value of the input sample squared; and

a multiplier element to obtain the product of (1) the difference between parameter R_m and the absolute value of the input sample squared and (2) the input sample;

10. (previously presented) The fractional-spaced equalizer as set forth in claim 9 wherein said algorithm forming the value R_m comprises:

an absolute value operator to perform an absolute value of the input modulated 2-tuple;

a divide operation to form the value of R_m ;

a switch S8 to control when the numerator portion of a ratio is to be delivered to the divide operation to form the value of parameter R_m ;

a switch S9 to control when the denominator portion of a ratio is to be delivered to the divide operation to form the value of parameter R_m ;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 9

a counter to control when switches S8 and S9 are closed to form the value of parameter R_m ;

a summing node used in the ratio's numerator accumulation process;

a summing node used in the ratio's denominator accumulation process;

a register element used in the ratio's numerator accumulation process;

a register element used in the ratio's denominator accumulation process;

a squaring operator;

a operator to perform a power operation to the m-th power; and

a parameter m representing the statistical moment of

the CMA update satisfies the condition $m > 0$;

11. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein said algorithm converting the ISI cancellation error signal into an adjustment signal comprises:

a complex conjugation operator to perform a complex conjugation of the samples of input error sequence;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 10

a parameter μ to control the adaptation rate of the equalizer's weight in accordance with the criterion for ISI cancellation; and
a multiplier element to form the product of the conjugated error sequence and parameter μ ;

12. (previously presented) The fractional-spaced equalizer as set forth in claim 11 wherein the value for said scalar μ is in the range $0 < \mu < \mu_{crit}$ and μ_{crit} is inversely proportional to the power level of the samples residing in the equalizer data register bank;

13. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein said algorithm driving the equalizer weight update comprises:

a bank of multiplier elements to scale each element in the data register bank with a sample of the ISI cancellation adjustment signal; and

a bank of summing nodes to form the addition of the said bank of products with the current contents of the equalizer weight register bank;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 11

14. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein constraint waveform is defined to be a high frequency signal;

15. (previously presented) The fractional-spaced equalizer as set forth in claim 14 wherein said high frequency signal representing said constraint waveform is sinusoidal in nature;

16. (previously presented) The fractional-spaced equalizer as set forth in claim 15 wherein said high frequency sinusoid signal is a complex sinusoid of the form $A \exp\{j 2\pi f kT_s + \phi\}$;

17. (previously presented) The fractional-spaced equalizer as set forth in claim 16 wherein said frequency f is a time variable frequency;

18. (previously presented) The fractional-spaced equalizer as set forth in claim 17 wherein minimum and maximum values of said time-variable frequency are selected to develop a robust out-of-band spectral mask for the FSE that is comparable to that of a MF.

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 12

19. (previously presented) The fractional-spaced equalizer as set forth in claim 16 wherein said amplitude A is an amplitude fixed to a singular value and satisfies $|A| > 0$;

20. (previously presented) The fractional-spaced equalizer as set forth in claim 16 wherein said amplitude A is a time variable amplitude A_s and satisfies $|A| > 0$;

21. (previously presented) The fractional-spaced equalizer as set forth in claim 16 wherein said phase ϕ is a phase fixed to a singular value and satisfies $\{0 \leq \phi < 2\pi\}$;

22. (previously presented) The fractional-spaced equalizer as set forth in claim 16 wherein said phase ϕ is a time variable phase and satisfies $\{0 \leq \phi < 2\pi\}$;

23. (previously presented) The fractional-spaced equalizer as set forth in claim 15 wherein said high frequency sinusoid signal is a real sinusoid, either of the form $A \sin\{2\pi f kT_s + \phi\}$ or $A \cos\{2\pi f kT_s + \phi\}$.

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 13

24. (previously presented) The fractional-spaced equalizer as set forth in claim 23 wherein said frequency f of said sinusoid is a time variable frequency;

25. (previously presented) The fractional-spaced equalizer as set forth in claim 24 wherein minimum and maximum values of said time-variable frequency f are selected to develop a robust out-of-band spectral mask for the FSE that is comparable to that of a MF.

26. (previously presented) The fractional-spaced equalizer as set forth in claim 23 wherein said amplitude A is an amplitude fixed to a singular value and satisfies $|A| > 0$;

27. (previously presented) The fractional-spaced equalizer as set forth in claim 23 wherein said amplitude A is a time variable amplitude A_s and satisfies $|A| > 0$;

28. (previously presented) The fractional-spaced equalizer as set forth in claim 23 wherein said phase ϕ is a phase fixed to a singular value and satisfies $\{0 \leq \phi < 2\pi\}$;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 14

29. (previously presented) The fractional-spaced equalizer as set forth in claim 23 wherein said phase ϕ is a time variable phase and satisfies $\{0 \leq \phi < 2\pi\}$;

30. (previously presented) The fractional-spaced equalizer as set for in claim 1 wherein said algorithm generating said constraint waveform comprises:

an overflow counter to generate an integer i that indexes a frequency register bank;

a frequency register bank storing the independent frequencies of the sinusoidal signal representing the constraint waveform;

a scalar set to value of 1.0;

a register that stores the state of the incremental count of the overflow counter;

an overflow test to compare the value in the register with a parameter representing a maximum count value;

a parameter N representing the number of independent constraint frequencies;

a summing node to increment the count of the overflow counter;
and

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 15

a quadrature oscillator that generates samples of the sinusoidal signal representing the constraint waveform from the frequencies in the frequency register bank;

31. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein samples of said constraint waveform are loaded into the constraint register bank via ROM lookup table;

32. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein value of said constraint level parameter β resides in the range $\{0 \leq \beta < 1\}$.

33. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein said differencing node forming constraint error is eliminated from the architecture of the present invention when parameter β is set to 0.

34. (previously presented) The fractional-spaced equalizer as set forth in claim 1 wherein said MF error adjustment algorithm comprises:

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 16

a complex conjugation operator to perform a complex conjugation of the samples of input MF constraint error;

a parameter α to control the adaptation rate of the equalizer's weight in accordance with the MF constraint criterion; and

a multiplier element to form the product of the complex conjugate MF constraint error and parameter α ;

35. (currently amended) The fractional-spaced equalizer as set forth in claim 34 wherein the value for [said] a scalar α satisfies $\alpha > 0$;

36. (previously presented) The fractional-spaced equalizer as set forth in claim 34 wherein the value for said scalar α is equal to A/L commensurate with the constraint waveform defined as a sinusoidal signal of amplitude A and length L ;

37. (currently amended) The fractional-spaced equalizer as set forth in claim 1 where [said] a fractional-spaced equalizer further comprises an algorithm that modifies the constraint waveform via time domain windowing;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 17

38. (previously amended) The fractional-spaced equalizer as set forth in claim 36 wherein said algorithm that modifies the constraint waveform via time domain windowing does so with a single window function;

39. (currently amended) The fractional-spaced equalizer as set forth in claim 38 wherein said [an] algorithm that modifies the constraint waveform via time domain windowing with a single window function comprises:

a bank of multiplier elements used to multiply each sample of the time series of each constraint sinusoid with a window function;

a set of coefficients representing a window function used to window the samples of the constraint sinusoid; and

a bank of register elements to store the set of coefficients representing the window function;

40. (previously presented) The fractional-spaced equalizer as set forth in claim 39 wherein said window function is derived from any function that can modify the time response of the constraint sinusoid through time-domain windowing;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 18

41. (previously presented) The fractional-spaced equalizer as set forth in claim 40 wherein said window function is derived from a rectangular, Bartlett, Blackman, Chebyshev, hamming, hann, Kaiser, or triangular window function;

42. (currently amended) The fractional-spaced equalizer as set forth in claim 37 wherein said [an] algorithm that modifies the constraint waveform via time domain windowing does so with multiple window functions;

43. (currently amended) The fractional-spaced equalizer as set forth in claim 42 wherein said [an] algorithm that modifies the constraint waveform via time domain windowing with multiple window functions comprises:

a register bank to store the samples of the current state of the windowed constraint waveform during the multi-window process;

a switch S10 to load the pre-windowed constraint waveform into the register bank only one time;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 19

a bank of multiplier elements used to multiply each sample of the time series of each constraint sinusoid with a particular window function of the set of window functions;

a collection of window functions used to window the samples of the constraint sinusoid;

a collection of banks of register elements to store the set of coefficients of the collection of window functions;

a switch S12 to allow the multiplier bank to access a particular window function of the set of window functions; and

a switch S11 to deliver the windowed constraint waveform to the constraint register bank when the windowing process has been completed;

44. (previously presented) The fractional-spaced equalizer as set forth in claim 43 wherein said window function is derived from a rectangular, Bartlett, Blackman, Chebyshev, hamming, hann, Kaiser, or triangular window function.

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 20

45. (currently amended) The fractional-spaced equalizer as set forth in claim 1 wherein [said] a fractional spaced equalizer further comprises an algorithm that controls the rate at which the contents of the equalizer's FF weight register bank are updated in accordance with the MF constraint update;

46. (previously presented) The fractional-spaced equalizer as set forth in claim 45 where said algorithm that controls the rate at which the contents of the equalizer's FF weight register bank are updated in accordance with the MF constraint criterion comprises:

a switch S3 to control when the algorithm for updating the contents of the equalizer FF weight registers is to be engaged;

an overflow counter to control when switch S3 is to be open and closed;

a scalar set to value of 1.0;

a register that stores the state of the incremental count of the overflow counter;

a summing node to increment the count of the overflow counter;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 21

an overflow test to compare the value in the register with a parameter representing a maximum count value;

a switch S4 to allow the overflow test to use the value designated by parameter P0 as the maximum count value;

a switch S5 to allow the overflow test to use the value designated by parameter P1 as the maximum count value;

a switch S6 to allow the overflow test to use the value designated by parameter P2 as the maximum count value;

a parameter P0 that represents a maximum count value;

a parameter P1 that represents a maximum count value; and

a parameter P2 that represents a maximum count value;

47. (previously presented) The fractional-spaced equalizer as set forth in claim 46 wherein said parameter P0, P1, and P2 are integers and satisfy $P0 > 0$, $P1 > 0$, and $P2 > 0$;

48. (currently amended) The fractional-spaced equalizer as set forth in claim 1 wherein [said] a fractional spaced equalizer further comprises an algorithm that initializes the contents of the equalizer's FF weight register bank with coefficients of $RRC\ MF[;]_{-}$

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 22

49. (previously presented) The fractional-spaced equalizer as set forth in claim 48 where said algorithm that initializes the contents of the equalizer's FF weight register bank with coefficients of a RRC MF comprises:

a selected set of RRC MF coefficients loaded from ROM into the register positions of the equalizer FF weight register bank; and

a switch S13 to shutoff the initialization after the contents of the equalizer FF weight register bank;

50. (currently amended) The fractional-spaced equalizer as set forth in claim 1 wherein [said] a fractional-spaced equalizer further comprises a decision-feedback update[;]_.

51. (previously presented) The fractional-spaced equalizer as set forth in claim 50 where said decision-feedback update comprises:

a register delay bank to store past decisions from a slicer device;

a slicer device to quantize samples of equalized decimated signal;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 23

a register bank representing the decision register bank that stores the values of the weights of a decision-feedback filter;

a bank of multiplier elements used in forming the inner product between the contents of the decision register bank and the decision-feedback weight register bank;

a bank of summing nodes used in forming the inner product between the contents of the decision register bank and the decision-feedback weight register bank;

a single summing node adding the decision register and decision-feedback weight inner product to the output of the M:1 commutator;

a bank of multiplier elements used in updating the contents of the decision-feedback weight register bank;

a bank of summing nodes in updating the contents of the decision-feedback weight register bank;

52. (currently amended) A method of performing [the] an inner product computation associated with [the] a MF constraint criterion, the method comprising the steps of:

using only [the] L_w central multiplier elements of the multiplier bank, where $L_w < L_e$, to multiply only L_w central samples of [the] a

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 24

constraint waveform with [the] contents of only [the] L_w central registers of [the] an equalizer FF weight register bank; and

using only [the] L_w central summing nodes of [the] a bank of summing nodes, where $L_w < L$, to add up the L_w products formed from multiplication of only the L_w central samples of the constraint waveform with the contents of only the L_w central registers of the equalizer FF weight register bank;

53. (currently amended) A fractional-spaced digital equalizer comprising:

a set of M banks of register delay elements representing data sub-register banks $\underline{u}_0, \underline{u}_1, \dots, \underline{u}_{(M-1)}$ that store [those] samples of the input distorted waveform which are commutated to data sub-register banks $\underline{u}_0, \underline{u}_1, \dots, \underline{u}_{(M-1)}$;

a set of M banks of register elements representing [the] an equalizer FF weight sub-register banks $\underline{w}_0, \underline{w}_1, \dots, \underline{w}_{(M-1)}$ that store the values of the equalizer's FF weights, with each bank storing a different subset of the total weight set;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 25

a set of M banks of register elements representing constraint sub-register banks $\underline{c}_0, \underline{c}_1, \dots, \underline{c}_{(M-1)}$ that store samples of [the] a constraint waveform;

an algorithm that generates samples of [a] the constraint waveform;

[a] the constraint waveform used in forming the inner product associated with the MF constraint processing;

a commutator COM 1 which delivers samples of the input distorted waveform to be equalized to data sub-register banks $\underline{u}_0, \underline{u}_1, \dots, \underline{u}_{(M-1)}$;

a switch S1 to control [that] a portion of [the] a joint ISI-cancellation and MF equalizer update associated with the ISI-cancellation process;

a bank of multiplier elements used in forming [the] inner products associated with both the ISI-cancellation and MF constraint updates;

a bank of summing nodes used in forming [the] inner products associated with both the ISI-cancellation and MF constraint updates;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 26

a single register delay element to store [the] inner products associated with the formation of the equalized signal;

a switch S14 to control when [the] an error sequence associated with ISI-cancellation is to be developed;

a switch S2 to control [that] a portion of the time-multiplexing process associated with the MF constraint update;

a single register delay element to store an inner product computation associated with [the] a MF constraint [processing] process;

a switch S15 to control when [the] a MF constraint error is to be developed;

a commutator COM 2 which controls which pair of sub-register banks, either $\{\underline{u}_0, \underline{c}_0\}$ or $\{\underline{u}_1, \underline{c}_1\}$... or $\{\underline{u}_{(M-1)}, \underline{c}_{(M-1)}\}$, are to access the multiplier bank at the current COM 1 position;

a commutator COM 3 which controls which equalizer FF weight sub-register bank, either w_0 or w_1 ... or $w_{(M-1)}$ is to access the multiplier bank at the current COM 1 position;

a clock to control [the] an adjustment of COM 1, COM 2, and COM 3;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 27

a summing node to add the two inner product sums which form the equalized signal;

an algorithm to form the error sequence associated with ISI cancellation;

an algorithm to convert the ISI cancellation error signal into an adjustment signal needed to control [the] an equalizer FF weight update in accordance with [the] a criterion for ISI cancellation;

an algorithm to update the contents of the equalizer FF weight sub-register banks $\{w_0, w_1, \dots, w_{(M-1)}\}$ in accordance with first, the criterion for ISI-cancellation, and second, [the] an MF constraint criterion;

a summing node to add the two inner product sums which form [the] a measure of orthogonality between the equalizer's weights and constraint waveform;

a parameter β representing [the] a constraint level of the MF processing;

a differencing node needed to subtract the orthogonality measure from the constraint level in order to form the constraint error;

an algorithm to convert the constraint error signal into an adjustment signal needed to control the equalizer FF weight update in accordance with the MF constraint criterion[;]_.

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 28

54. (currently amended) The fractional-spaced equalizer as set forth in claim 53 wherein [said] a poly-phase configured equalizer accommodates an input signal sampled at M-samples-per-symbol by using M data sub-register banks, M constraint register sub-banks, and M equalizer FF weight register banks[;]_.

55. (previously presented) The fractional-spaced equalizer as set forth in claim 54 wherein said sampling factor M is equal to 2;

56. (previously presented) The fractional-spaced equalizer as set forth in claim 53 wherein said equalizer operates as a complex equalizer comprising complex operations;

57. (previously presented) The fractional-spaced equalizer as set forth in claim 53 wherein said equalizer operates as a real equalizer comprising real operations;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 29

58. (previously presented) The fractional-spaced equalizer as set forth in claim 53 wherein said algorithm that computes the error associated with ISI cancellation is based upon a training sequence update and comprises:

- a training sequence of distortion-less data; and
- a differencing node to form the difference between the equalized decimated signal and the training sequence;

59. (previously presented) The fractional-spaced equalizer as set forth in claim 53 wherein said algorithm that computes the error associated with ISI cancellation is based upon a decision-directed update and comprises:

- a slicer device to quantize samples of equalized decimated signal; and
- a differencing node to form the difference between pre-slicer sequence and post-slicer sequence;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 30

60. (currently amended) The fractional-spaced equalizer as set forth in claim 53 wherein said algorithm that computes the error associated with ISI cancellation is based upon [the] a blind CMA update and comprises:

an algorithm to form the statistical parameter R_m measuring the ratio of moments of the pre-pulse shaped modulation amplitudes;

a switch $S7$ to eliminate the computation of R_m from the processing so that parameter R_m is computed only one time;

a register element to store the value of parameter R_m ;

a complex conjugation operator to conjugate the sample input to the CMA;

a multiplier element to obtain the product between the input sample and its complex conjugate;

a differencing node to form the difference between parameter R_m and the absolute value of the input sample squared; and

a multiplier element to obtain the product of (1) the difference between parameter R_m and the absolute value of the input sample squared and (2) the input sample[;]_.

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 31

61. (previously presented) The fractional-spaced equalizer as set forth in claim 60 wherein said algorithm forming the value R_m comprises:

an absolute value operator to perform an absolute value of the input modulated 2-tuple;

a divide operation to form the value of R_m ;

a switch S8 to control when the numerator portion of a ratio is to be delivered to the divide operation to form the value of parameter R_m ;

a switch S9 to control when the denominator portion of a ratio is to be delivered to the divide operation to form the value of parameter R_m ;

a counter to control when switches S8 and S9 are closed to form the value of parameter R_m ;

a summing node used in the ratio's numerator accumulation process;

a summing node used in the ratio's denominator accumulation process;

a register element used in the ratio's numerator accumulation process;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 32

a register element used in the ratio's denominator accumulation process;

a squaring operator;

a operator to perform a power operation to the m-th power; and

a parameter m representing the statistical moment of the CMA update satisfies the condition $m > 0$;

62. (previously presented) The fractional-spaced equalizer as set forth in claim 54 wherein said algorithm converting the ISI cancellation error signal into an adjustment signal comprises:

a complex conjugation operator to perform a complex conjugation of the samples of input error sequence;

a parameter μ to control the adaptation rate of the equalizer's weight in accordance with the criterion for ISI cancellation; and

a multiplier element to form the product of the conjugated error sequence and parameter μ ;

63. (currently amended) The fractional-spaced equalizer as set forth in claim 62 wherein the value for said [scalar] parameter μ is in the range $0 < \mu < \mu_{crit}$ and μ_{crit} is inversely proportional to

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 33

the power level of the samples of distorted waveform residing in the equalizer data register bank[;]_.

64. (previously presented) The fractional-spaced equalizer as set forth in claim 53 wherein said algorithm driving the equalizer weight update comprises:

a bank of multiplier elements to scale each element in the data register bank with a sample of the ISI cancellation adjustment signal; and

a bank of summing nodes to form the addition of the said bank of products with the current contents of the equalizer weight register bank;

65. (previously presented) The fractional-spaced equalizer as set forth in claim 53 wherein constraint waveform is defined to be a high frequency signal;

66. (previously presented) The fractional-spaced equalizer as set forth in claim 65 wherein said high frequency signal representing said constraint waveform is sinusoidal in nature;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 34

67. (previously presented) The fractional-spaced equalizer as set forth in claim 66 wherein said high frequency sinusoid signal is a complex sinusoid of the form $A \exp\{ j 2\pi f kT_s + \phi \}$;

68. (previously presented) The fractional-spaced equalizer as set forth in claim 67 wherein said frequency f is a time variable frequency;

69. (previously presented) The fractional-spaced equalizer as set forth in claim 68 wherein minimum and maximum values of said time-variable frequency are selected to develop a robust out-of-band spectral mask for the FSE that is comparable to that of a MF;

70. (previously presented) The fractional-spaced equalizer as set forth in claim 67 wherein said amplitude A is an amplitude fixed to a singular value and satisfies $|A| > 0$;

71. (previously presented) The fractional-spaced equalizer as set forth in claim 67 wherein said amplitude A is a time variable amplitude and satisfies $|A| > 0$;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 35

72. (previously presented) The fractional-spaced equalizer as set forth in claim 67 wherein said phase ϕ is a phase fixed to a singular value and satisfies $\{0 \leq \phi < 2\pi\}$;

73. (previously presented) The fractional-spaced equalizer as set forth in claim 67 wherein said phase ϕ is a time variable phase and satisfies $\{0 \leq \phi < 2\pi\}$;

74. (previously presented) The fractional-spaced equalizer as set forth in claim 66 wherein said high frequency sinusoid signal is a real sinusoid, either of the form $A \sin\{2\pi f kT_s + \phi\}$ or $A \cos\{2\pi f kT_s + \phi\}$;

75. (previously presented) The fractional-spaced equalizer as set forth in claim 74 wherein said frequency f of said sinusoid is a time variable frequency;

76. (previously presented) The fractional-spaced equalizer as set forth in claim 75 wherein minimum and maximum values of said time-variable frequency are selected to develop a robust out-of-

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 36

band spectral mask for the FSE that is comparable to that of a MF;

77. (previously presented) The fractional-spaced equalizer as set forth in claim 74 wherein said amplitude A is an amplitude fixed to a singular value and satisfies $|A| > 0$;

78. (previously presented) The fractional-spaced equalizer as set forth in claim 74 wherein said amplitude A is a time variable amplitude and satisfies $|A| > 0$;

79. (previously presented) The fractional-spaced equalizer as set forth in claim 74 wherein said phase ϕ is a phase fixed to a singular value and satisfies $\{0 \leq \phi < 2\pi\}$;

80. (previously presented) The fractional-spaced equalizer as set forth in claim 74 wherein said phase ϕ_s is a time variable phase and satisfies $\{0 \leq \phi < 2\pi\}$;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 37

81. (currently amended) The fractional-spaced equalizer as set forth in claim 53 wherein [said] a sinusoid representing said constraint waveform is generated via an algorithm comprising of:

an overflow counter to generate an integer i that indexes a frequency register bank;

a frequency register bank storing the independent frequencies of the sinusoidal signal representing the constraint waveform;

a scalar set to value of 1.0;

a register that stores the state of the incremental count of the overflow counter;

an overflow test to compare the value in the register with a parameter representing a maximum count value;

a parameter N representing the number of independent constraint frequencies;

a summing node to increment the count of the overflow counter;
and

a quadrature oscillator that generates samples of the sinusoidal signal representing the constraint waveform from the frequencies in the frequency register bank[;]_.

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 38

82. (currently amended) The fractional-spaced equalizer as set forth in claim 53 wherein samples of [said] a sinusoidal constraint waveform are loaded into the constraint register bank via ROM lookup table[;]_.

83. (previously presented) The fractional-spaced equalizer as set forth in claim 53 wherein value of said constraint level parameter β resides in the range $\{0 \leq \beta < 1\}$;

84. (currently amended) The fractional-spaced equalizer as set forth in claim 53 wherein said differencing node forming constraint error is eliminated from the architecture of the present invention when a parameter β is set to 0[;]_.

85. (previously presented) The fractional-spaced equalizer as set forth in claim 53 wherein said MF error adjustment algorithm comprises:

a complex conjugation operator to perform a complex conjugation of the samples of input MF constraint error;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 39

a parameter α to control the adaptation rate of the equalizer's weight in accordance with the MF constraint criterion; and

a multiplier element to form the product of the complex conjugate MF constraint error and parameter α ;

86. (currently amended) The fractional-spaced equalizer as set forth in claim 85 wherein the value for [said] a scalar α satisfies $\alpha > 0$ [;] _.

87. (previously presented) The fractional-spaced equalizer as set forth in claim 86 wherein the value for said scalar α is equal to A/L commensurate with the constraint waveform defined as a sinusoidal signal of amplitude A and length L ;

88. (currently amended) The fractional-spaced equalizer as set forth in claim 53 wherein [said] a fractional-spaced equalizer further comprises an algorithm that modifies the constraint waveform via time-domain windowing [;] _.

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 40

89. (currently amended) The fractional-spaced equalizer as set forth in claim 88 wherein said [an] algorithm that modifies the constraint waveform via time-domain windowing does so with a single window function;

90. (previously presented) The fractional-spaced equalizer as set forth in claim 89 wherein said algorithm that modifies the constraint waveform via time domain windowing with a single window function comprises:

a bank of multiplier elements used to multiply each sample of the time series of each constraint sinusoid with a window function;
and

a set of coefficients representing a window function used to window the samples of the constraint sinusoid; and

a bank of register elements to store the set of coefficients representing the window function;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 41

91. (previously presented) The fractional-spaced equalizer as set forth in claim 90 wherein said window function is derived from any function that can modify the time response of the constraint sinusoid through time-domain windowing;

92. (previously presented) The fractional-spaced equalizer as set forth in claim 91 wherein said window function is derived from a rectangular, Bartlett, Blackman, Chebyshev, hamming, hann, Kaiser, or triangular window function;

93. (currently amended) The fractional-spaced equalizer as set forth in claim 88 wherein said [an] algorithm that modifies the constraint waveform via time domain windowing does so with multiple window functions[;]_.

94. (previously presented) The fractional-spaced equalizer as set forth in claim 93 wherein said an algorithm that modifies the constraint waveform via time domain windowing with multiple window functions comprises:

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 42

a register bank to store the samples of the current state of the windowed constraint waveform during the multi-window process;

a switch S10 to load the pre-windowed constraint waveform into the register bank only one time;

a bank of multiplier elements used to multiply each sample of the time series of each constraint sinusoid with a particular window function of the set of window functions;

a collection of window functions used to window the samples of the constraint sinusoid;

a collection of banks of register elements to store the set of coefficients of the collection of window functions;

a switch S12 to allow the multiplier bank to access a particular window function of the set of window functions; and

a switch S11 to deliver the windowed constraint waveform to the constraint register bank when the windowing process has been completed;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 43

95. (previously presented) The fractional-spaced equalizer as set forth in claim 94 wherein said window function is derived from a rectangular, Bartlett, Blackman, Chebyshev, hamming, hann, Kaiser, or triangular window function;

96. (currently amended) The fractional-spaced equalizer as set forth in claim 53 wherein [said] a fractional spaced equalizer further comprises an algorithm that controls the rate at which the contents of the equalizer's FF weight register bank are updated in accordance with the MF constraint update[;]_.

97. (previously presented) The fractional-spaced equalizer as set forth in claim 96 where said algorithm that controls the rate at which the contents of the equalizer's FF weight register bank are updated in accordance with the MF constraint update comprises:

a switch S3 to control when the algorithm for updating the contents of the equalizer FF weight registers is to be engaged;

an overflow counter to control when switch S3 is to be open and closed;

a scalar set to value of 1.0;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 44

a register that stores the state of the incremental count of the overflow counter;

a summing node to increment the count of the overflow counter;

an overflow test to compare the value in the register with a parameter representing a maximum count value;

a switch S4 to allow the overflow test to use the value designated by parameter P0 as the maximum count value;

a switch S5 to allow the overflow test to use the value designated by parameter P1 as the maximum count value;

a switch S6 to allow the overflow test to use the value designated by parameter P2 as the maximum count value;

a parameter P0 that represents a maximum count value;

a parameter P1 that represents a maximum count value; and

a parameter P2 that represents a maximum count value;

98. (previously presented) The fractional-spaced equalizer as set forth in claim 97 wherein said parameters P0, P1, and P2 are integers and satisfy $P0 > 0$, $P1 > 0$, and $P2 > 0$;

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 45

99. (currently amended) The fractional-spaced equalizer as set forth in claim 53 wherein [said] a fractional spaced equalizer further comprises an algorithm that initializes the contents of the equalizer's FF weight register bank with coefficients of RRC MF[;].

100. (previously presented) The fractional-spaced equalizer as set forth in claim 99 where said algorithm that initializes the contents of the equalizer's FF weight register bank with coefficients of a RRC MF comprises:

a selected set of RRC MF coefficients loaded from ROM into the register positions of the equalizer FF weight register bank; and

a switch S13 to shutoff the initialization after the contents of the equalizer FF weight register bank;

101. (currently amended) The fractional-spaced equalizer as set forth in claim 53 wherein [said] a fractional-spaced equalizer further comprises a decision-feedback update[;].

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 46

102. (previously presented) The fractional-spaced equalizer as set forth in claim 101 where said decision-feedback update comprises:

a register delay bank to store past decisions from a slicer device;

a slicer device to quantize samples of equalized decimated signal;

a register bank representing the decision register bank that stores the values of the weights of a decision-feedback filter;

a bank of multiplier elements used in forming the inner product between the contents of the decision register bank and the decision-feedback weight register bank;

a bank of summing nodes used in forming the inner product between the contents of the decision register bank and the decision-feedback weight register bank;

a single summing node adding the decision register and decision-feedback weight inner product to the output of the 2:1 commutator;

a bank of multiplier elements used in updating the contents of the decision-feedback weight register bank; and

Appln. No. 09/905,722

Amendment Date: August 21, 2005

Reply to Office Action of April 21, 2005

Page 47

a bank of summing nodes in updating the contents of the
decision-feedback weight register bank;

103. Cancel.